

## 2. Headlight and Tail Light System

### A: WIRING DIAGRAM

#### 1. HEADLIGHT

<Ref. to WI-105, WIRING DIAGRAM, Headlight System.>

#### 2. CLEARANCE LIGHT AND ILLUMINATION LIGHT

<Ref. to WI-114, WIRING DIAGRAM, Clearance Light and Illumination Light System.>


### B: INSPECTION

#### 1. HEADLIGHT SWITCH

<Ref. to LI-9, INSPECTION, Combination Switch (Light).>

#### 2. HEADLIGHT RELAY


Measure the headlight relay resistance between terminals when connecting terminal No. 4 to the battery positive terminal and terminal No. 3 to the battery ground terminal.



Continuity	Terminal No.	Standard
Yes	1 and 2	Less than 1 Ω
No		1 MΩ or more

#### 3. TAIL AND ILLUMINATION RELAY

Measure the resistance between tail and illumination relay terminals when connecting terminal No. 4 to the battery positive terminal and terminal No. 3 to the battery ground terminal.



Continuity	Terminal No.	Standard
Yes	1 and 2	Less than 1 Ω
No		1 MΩ or more