

# Back-up Light System

LIGHTING SYSTEM

## 5. Back-up Light System

### A: WIRING DIAGRAM


#### 1. BACK-UP LIGHT

<Ref. to WI-112, WIRING DIAGRAM, Back-up Light System.>

### B: INSPECTION

#### 1. BACK-UP LIGHT SWITCH (MT MODEL)

Measure the back-up light switch resistance.




(A) Non-turbo model

(B) Turbo model

Switch position	Terminal No.	Standard
When shift lever is set in reverse position	Non-turbo model: 1 and 2 Turbo model: 2 and 4	Less than 1 Ω
Other positions		1 MΩ or more

#### 2. INHIBITOR SWITCH (AT MODEL)

Measure the inhibitor switch resistance.



Switch position	Terminal No.	Standard
When the shift lever is in "R" range	1 and 2	Less than 1 Ω
Other positions		1 MΩ or more